





TEMPERATURE REGULATORS SELF ACTING, NON BALANCED, SINGLE SEAT TR25/R (Reverse action for cooling systems)

DESCRIPTION

The TR25/R valves series are designed for temperature control of cooling systems where the valve opens with temperature rise. They are single seated and are intended to be coupled with T series thermostat models T.205 and T.405. The liquid filling the thermostat expands when the temperature of the fluid being cooled rises, opening the valve.

MAIN FEATURES

Easily adjustable temperature range.

Proportional temperature control.

Single seated, two way, reverse acting valve.

Leakage < 0,05% Kvs.

Built-in strainer.

Narrow thermostat neutral zone (1,5 °C - 2,5 °C).

No special tools required for servicing.

Stuffing box is an integral part of the thermostatic element, allowing easy and simple maintenance of the valve.

OPTIONS: PK sensor pocket.

Diffferent capillary lenghts.
Other thermostats on request.

USE: Water, air ad other gases and liquids compatible

with the construction.

AVAILABLE

VALVES: TR25S/R – carbon steel.

TR25I/R - stainless steel.

AVAILABLE

THERMOSTATS: T.205 - 200 N (max. closing force).

T.405 – 400 N (max. closing force).

SIZES: 1/2" to 1"; DN 15 to DN 25.

CONNECTIONS: Female threaded ISO 7 Rp.

Flanged EN 1092-1 PN 40.

THERMOSTAT

RANGES: T.205: 0 to 60 °C, 30 to 90 °C and 60 to 120 °C.

T.405: 0 to 120 °C and 40 to 160 °C.

INSTALLATION: Horizontal installation with the thermostat in the


vertical position, in order to reduce wear.

A "Y" strainer should be installed upstream of the

valve.

See IMI - Installation and maintenance

instructions.







PK sensor pocket

BODY LIMITING CONDITIONS				
PN 40 RELATED				
ALLOWABLE PRESSURE	TEMPERATURE			
40 bar	120 °C			
24 bar	350 °C			

Minimum working temperature: -10 °C. Maximum working temperature: 150 °C.





TECHNICAL DATA						
TYPE	CONNECTION	OPENING Ø	Kvs (m³/h)	STROKE		
TR25 – 15/15	DN 15	15 mm	1,9	6 mm		
TR25 – 20/15	DN 20	15 mm	1,9	6,5 mm		
TR25 - 20/20	DN 20	20 mm	4,2	6,5 mm		
TR25 - 25/20	DN 25	20 mm	4,2	7 mm		

MAX. PERMISSIBLE DIFFERENTIAL PRESSURES					
		T.205	T.405 DIFFERENTIAL PRESSURE		
SIZE	SEAT Ø	DIFFERENTIAL PRESSURE			
DN 15	15 mm	5,3 bar	15 bar		
DN 20	15 mm	5,3 bar	15 bar		
DN 20	20 mm	2,9 bar	9 bar		
DN 25	20 mm	2,9 bar	9 bar		

PROPORTIONAL BAND


The proportional band is the temperature change required for the valve to move from its fully open to fully closed position. It depends on the valve stroke (mm) and on the thermostat movement per °C (mm/°C), and is calculated as follows:


Proportional band: Valve stroke (mm)
Thermostat mov. (mm/°C)

Thermostat movement for T.205 and T.405: 0,5 mm/°C

A proportional band between 8 °C and 13 °C is suitable for most applications. A smaller proportional band is not ideal when heat loads vary rapidly.

DIMENSIONS (mm) – THERMOSTAT						
TYPE A B C E					WEIGHT (kg)	
T.205	305	405	210	22	1,8	
T.405	385	525	390	22	2,6	





DIMENSIONS (mm) – VALVE BODY								
THREADED						PN 40		
SIZE	A	В	С	F	WEIGHT (kg)	D	E	WEIGHT (kg)
1/2"	90	40	70	50	1,2	130	47,5	2,6
3/4"	90	40	70	50	1,2	150	52,5	3,2
* 3/4"	100	45	75	55	1,6	150	52,5	3,6
1"	100	45	75	55	1,6	160	57,5	4,2


^{*} TR25 - 20/20 model only.








MATERIALS					
POS.	DESIGNATION	TR25S/R	TR25I/R		
1	Body	P250GH / 1.0460	AISI 316 / 1.4401		
2	Bonnet	C45E / 1.1191	AISI 316L / 1.4404; AISI 303 / 1.4305		
3	* Gasket	St. steel / Graphite	St. steel / Graphite		
4	* Valve plug	St. steel / EPDM	St. steel / EPDM		
5	Seat	AISI 316 / 1.4401	AISI 316 / 1.4401		
6	* Spring	AISI 302 / 1.4300	AISI 302 / 1.4300		
7	Сар	AISI 316 / 1.4401	AISI 316 / 1.4401		
8	* Cap gasket	St. steel / Graphite	St. steel / Graphite		



PK SENSOR POCKETS

Sensor pockets made of stainless steel can be supplied with all TR series self-acting thermostats using rod sensors. A sensor pocket, also called thermowell, is used to protect the sensor and to allow its removal while the plant is running or, e.g., the tank where it is connected to is full. The use of sensor pockets implies delay of heat transfer to the rod sensors and, thus, a longer thermostat reaction time. This is, to some extent, counteracted by filling up the sensor pockets with a thermal conductive paste or glycerine.



INSTALLATION

The installation site for the sensor pocket is arbitrary when paste is applied. When glycerine is used, the sensor pocket must point at least slightly downwards.

MATERIAL

AISI 316 / 1.4401.

DIMENSIONS (mm)						
TYPE	D	Н	L	S	R	
PK2	25	9	218	36	1"	
PK4	25	10	390	45	11/4"	



^{*} Available spare parts.